



CONSOLE CONNECTOR KIT SE-CCK8000

FOR USE WITH: HAMMOND Models A, B, C, D, E, BV, CV, B-2, B-3, C-2, C-3, RT-2, RT-3  
 LESLIE Speakers: 122, 122V, 122RV, 142, 222, 222RV

INTRODUCTION

This kit contains the Speakeasy 122 Console Connector. When properly installed to a Hammond tonewheel console, it provides control and proper connection for model 122 type Leslie tone cabinets (122, 142, 21H, 22H, 222, etc.)

**CAUTION:** Due to the presence of electrical potential, only an experienced technician should perform installation procedures or adjustments involving 110vac or 220vac "mains" power.

**NOTE:** The connector chassis should be installed in a location where the wires can reach their destinations. In the event of connecting to a distant outlet (like one in a B3 outlet box) the included pigtail may need to be spliced to the original outlet wiring.

**WARNING:** Always inspect console wiring to make sure it is in safe and serviceable condition before any accessory installation.

Wire Color	Description	Connection
Blue & Grey Twisted Pair	AC Mains	To Blue and Grey wires on Pre-amp AC panel
Red & Black Twisted Pair	GG Terminals	One to each "G" terminal on Preamp
Yellow	Chassis Ground	Place under a chassis screw
Brown	Speed Switch	Connect to "Half-Moon" or other appropriate SPST switch.